



RT-REL Power Sensing Relay



NEED A DRY CONTACT CLOSURE?

Plug the power cord of the RT-REL into a switched AC outlet. In its unpowered state, there is an internal contact between the C (common) and NC (normally closed) terminals on the unit. When 120VAC power is applied to the power cord, connection is opened between C and NC and closed between C and NO (normally open).

The RT-REL can be used with any product that needs a contact closure to activate, including the Juice Goose SQ-1500.

A common application for the RT-REL is to extend the use of a switched electrical outlet on a rack mounted power strip or sequencer or on some other device such as an audio receiver or amplifier. When plugged into the switched outlet the RT-REL can close and open a dry contact on the three position terminal strip.

SPECIFICATIONS	
CHASSIS	Durable Plastic (Black)
DIMENSIONS (Inches).....	3 x 2 x 1
WEIGHT (Ounces).....	4.8
POWER CABLE	3 Feet, 18/2 AWG with NEMA 5-15P
RELAY CONTACT RATING (Amps)	10

7320 Ashcroft, Suite 104
Houston, Texas 77081
713.772.1404
info@juicegoose.com